

Attorney Docket No. 36856.527

CONDUCTOR PATTERN AND ELECTRONIC COMPONENT HAVING THE SAME

BACKGROUND OF THE INVENTION

1. Field of the Invention

The present invention relates to a conductor pattern and an electronic component including the conductor pattern.

2. Description of the Related Art

In a conventional conductor pattern for an inductor formed by printing conductive paste, a pattern with a small width cannot be obtained and is not suitable for an inductor having a small deviation. When manufacturing the inductor with a small deviation, a conductive thin film is formed by sputtering, a conductor pattern for an inductor is formed by the combination of photo-lithography and etching. Then, the film thickness is further increased by plating so as to form a conductor pattern for an inductor having a small deviation and a large Q value. The plating process has a problem, however, of a long throughput time and a greatly increased cost.

Recently, a method using photosensitive conductive paste has been proposed for forming a conductor pattern. In this method, photosensitive conductive paste is coated and a

conductor pattern is formed thereon by exposing, developing, and burning it.

When a pattern width and space of the conductor pattern for forming an inductor are reduced and further when an aspect ratio is increased by an increase of the conductor thickness in order to obtain the required Q value and a DC resistance, a deficiency occurs in that a spiral corner of the conductor pattern for the inductor is peeled and raised off a substrate during burning. This occurs because of the cross-sectional shape and stress of contraction during the burning required when using photosensitive conductive paste.

That is, a light beam such as a UV beam is attenuated gradually in the photosensitive conductive paste, so that a bottom portion of the photosensitive conductive paste is difficult to be exposed. A photo-cured area is therefore reduced gradually toward a lower portion, and as shown in Fig. 14, a cross-sectional shape of a conductor pattern 31 after development is generally liable to be an inverted trapezoid. A contraction rate of the conductor pattern 31 after burning is approximately 70% and a contact area between a substrate 30 and the conductor pattern 31 is further reduced. Therefore, the contact area between the substrate 30 and the conductor pattern 31 is comparatively small and a joining strength between the substrate 30 and the conductor pattern 31 is also comparatively small.

On the other hand, for a conductor pattern 32 for the inductor having straight lines 32a and corners 32b shown in Fig. 15, a large contraction stress K1 is produced on the lines 32a during burning. On the corners 32b, a large tensile stress K2 is produced in the width direction of the pattern due to the contraction stress K1 of the straight line 32a, so that the corner 32b is likely to be peeled and raised off the substrate 30 (see the conductor pattern 31 on the right side of Fig. 14).

SUMMARY OF THE INVENTION

In order to solve the problems described above, preferred embodiments of the present invention provide a conductor pattern that prevents corners from peeling and raising off a substrate, and an electronic component including such an improved conductor pattern.

According to a preferred embodiment of the present invention, a conductor pattern according to the present invention is formed from photo-sensitive conductive paste coated on a surface of a substrate by exposing, developing, and burning the photo-sensitive conductive paste, and the conductor pattern includes straight lines and corners connected to the straight lines, wherein the bottom surface cross-sectional width of the conductor pattern is not larger than the top surface cross-sectional width thereof, and

wherein the bottom surface cross-sectional width of each of the corners is larger than the bottom surface cross-sectional width of each of the straight lines.

More specifically, the bottom surface cross-sectional width of each of the corners may preferably be at least about 1.07 times, more preferably at least about 1.5 times, that of the conductor thickness of each of the corners. Furthermore, the bottom surface cross-sectional width of each of the straight lines may preferably be at least about 0.67 times that of the conductor thickness of each of the straight lines.

With the unique construction and structure described above, the bottom surface cross-sectional width of the corner is larger than the bottom surface cross-sectional width of the straight line, so that the contact area between the corner and a substrate is increased compared with conventional conductor pattern. Thereby, the problems with conventional conductor patterns are solved.

An electronic component according to another preferred embodiment of the present invention includes a conductor pattern formed from photo-sensitive conductive paste coated on a surface of a substrate by exposing, developing, and burning the photo-sensitive conductive paste, and the conductor pattern includes straight lines and corners connected to the straight lines, wherein the conductor

pattern is any one of conductor patterns having the features described above with respect to the first preferred embodiment of the present invention.

Other features, elements, characteristics, and advantages of the present invention will become more apparent from the detailed description of preferred embodiments thereof with reference to the attached drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1 is a plan view of a conductor pattern according to a preferred embodiment of the present invention;

Fig. 2 is a cross-sectional view along the line II-II of Fig. 1;

Fig. 3 is a perspective view of the conductor pattern shown in Fig. 1, showing a manufacturing process thereof;

Fig. 4 is a perspective view showing a manufacturing process continued from that shown in Fig. 3;

Fig. 5 is a cross-sectional view showing a manufacturing process continued from that shown in Fig. 4;

Fig. 6 is a perspective view showing a manufacturing process continued from that shown in Fig. 5;

Fig. 7 is a perspective view showing a manufacturing process continued from that shown in Fig. 6;

Fig. 8 is a perspective view showing a manufacturing process continued from that shown in Fig. 7;

Fig. 9 is a perspective view showing a manufacturing process continued from that shown in Fig. 8;

Fig. 10 is a perspective view showing a manufacturing process continued from that shown in Fig. 9;

Fig. 11 is a perspective view showing a manufacturing process continued from that shown in Fig. 10;

Fig. 12 is a perspective view showing a manufacturing process continued from that shown in Fig. 11;

Fig. 13 is a perspective view showing a manufacturing process continued from that shown in Fig. 12;

Fig. 14 is a cross-sectional view of a conventional conductor pattern; and

Fig. 15 is a plan view of the conductor pattern shown in Fig. 14.

DETAILED DESCRIPTION OF PREFERRED EMBODIMENTS

Preferred embodiments of a conductor pattern and an electronic component having the conductor pattern according to the present invention will be described below with reference to the attached drawings. Preferred embodiments will be described using a conductor pattern for an inductor and the inductor as examples. However, the present invention is not limited to inductors and may be applied to any electronic device including a conductor pattern.

As shown in Fig. 1, a conductor pattern 5 for an

inductor preferably has a substantially spiral configuration and includes straight lines 5a and corners 5b connected to the straight lines 5a. As shown in Fig. 2, the cross-sectional bottom surface width W1 of the conductor pattern 5 for the inductor is substantially equal to or smaller than the top surface width W2 thereof. The bottom surface cross-sectional width W1 of the corner 5b is preferably larger than the bottom surface cross-sectional width W1 of the straight line 5a. Accordingly, the contact area between the corner and a substrate is greatly increased compared with conventional conductor. Thereby, the corner 5b of the conductor pattern 5 for the inductor is prevented from being peeled off or removed from the substrate during burning.

The conductor pattern 5 for the inductor is preferably formed as follows.

As shown in Fig. 3, on the substantially entire top surface of a substrate 1, photosensitive conductive paste 2 is coated by a method such as a printing method and dried so as to form a film. In the present preferred embodiment, a targeted thickness of the photosensitive conductive paste 2 after drying is, for example, about 15 μm . The substrate 1 is preferably made from a material such as glass, glass ceramic, alumina, and ferrite, or other suitable material. For the photosensitive conductive paste 2, a material such as Ag or Cu is preferably used, although other suitable

materials could be used.

Then, as shown in Figs. 4 and 5, on the top surface of the substrate 1, a photo-mask 3 having predetermined image patterns 3a formed thereon in a matrix arrangement is covered, and a UV beam B is applied thereto, so that a desired portion of the photosensitive conductive paste 2 is photo-cured (an exposure process). Since it is difficult for the UV beam B to reach a lower portion of the photosensitive conductive paste 2 at this time, as shown in Fig. 5, a photo-cured area 2a is gradually reduced along the thickness thereof. In addition, an area 2c from which the UV beam B is shielded by a non-light-transmissive portion 3b of the photo-mask 3 is a non-photo-cured area. In the image pattern 3a of the photo-mask 3, the width of the corner is larger than that of the straight line.

Then, the photosensitive conductive paste 2 is developed by spraying liquid developer on the surface of the substrate 1. Thus, the non-photo-cured area 2c of the photosensitive conductive paste 2 is removed by the liquid developer. The residual photosensitive conductive paste 2 is arranged to define the substantially spiral conductor pattern 5 for the inductor. A cross-sectional shape of the conductor pattern 5 for the inductor is preferably a substantially inverted trapezoid. However, the shape may also be a substantially rectangular one. The conductor

patterns 5 for the inductor are arranged on the surface of the substrate 1 in a matrix arrangement, as shown in Fig. 6.

Subsequently, the conductor patterns 5 for the inductor are burned by heat treatment at a high temperature (about 800°C, for example). At this time, as shown in Fig. 1, a large contraction stress K1 is produced on the straight line 5a of the conductor pattern 5. In the corner 5b, a large tensile stress K2 is generated due to the contraction stress K1. However, since the bottom surface cross-sectional width W1 of the corner 5b of the conductor pattern 5 is larger than the bottom surface cross-sectional width W1 of the straight line 5a so that a joining strength between the corner 5b and the substrate 1 is very large, even when the tensile stress K2 is applied thereto, the corner 5b cannot be peeled off the substrate 1.

Furthermore, as shown in Fig. 7, on the substantially entire top surface of the substrate 1 having the conductor patterns 5 for the inductor disposed thereon, photosensitive insulating paste 8 is coated preferably using a method such as a printing method and dried so as to form a film. For the photosensitive insulating paste 8, a material such as a polyimide resin is used.

Then, as shown in Fig. 8, on the top surface of the substrate 1, a photo-mask 9 having predetermined image patterns 9a formed thereon is covered, and a UV beam or

other suitable light source is applied thereto, so that the photosensitive insulating paste 8 except a portion of via holes is cured via an exposure process. Then, the substrate 1 is developed under substantially the same conditions as those of the conductor pattern 5 for the inductor. Thus, an unnecessary portion of the photosensitive insulating paste 8 is removed by liquid developer so as to form via holes 11 (see Fig. 9). The residual photosensitive insulating paste 8 is arranged to define an insulating film 10. Subsequently, the insulating film 10 having via holes 11 is fired by heat treatment at a high temperature. One end of the conductor patterns 5 for the inductor is exposed at the via hole 11.

Next, as shown in Fig. 10, on the substantially entire top surface of the insulating film 10 having the via holes 11 formed thereon, photosensitive conductive paste 15 is coated preferably by a method such as a printing method and dried so as to form a film. Then, as shown in Fig. 11, on the top surface of the substrate 1, a photo-mask 16 having predetermined image patterns 16a formed thereon in a matrix arrangement is covered, and a UV beam is applied thereto so that a desired portion of the photosensitive conductive paste 15 is cured via an exposure process.

Next, the substrate 1 is developed under the same conditions as those of the conductor pattern 5 for the inductor. Thus, an unnecessary portion of the

photosensitive conductive paste 15 except the desired portion is removed by liquid developer (a developing process). The residual photosensitive conductive paste 15 is arranged to define the spiral conductor patterns 17 for the inductor as shown in Fig. 12. One end of each conductor pattern 17 for the inductor is electrically connected to the one end of each conductor pattern 5 for the inductor through the via hole 11.

In the same manner, the insulating film and the conductor pattern for the inductor are alternately deposited on each other. The conductor patterns 5 and 17 for the inductor are electrically connected in series through the via holes 11 formed in the insulating film 10 so as to define a coil. After depositing a protecting film on the top layer, the substrate 1 is cut into independent chip components. As is shown in Fig. 13, at both ends of the chip 22, external electrodes 23 and 24 are formed by using a method such as coating, sputtering, and wet plating, or other suitable method. The external electrodes 23 and 24 are connected to both ends of the coil, respectively. In such a manner, a multi-layer inductor 25 is obtained.

In addition, a conductor pattern and an electronic component including the conductor pattern according to various preferred embodiments of the present invention are limited to that described above, and instead, the conductor






pattern and the electronic component including the conductor pattern may be modified within the scope of the present invention.

Preferred embodiments have been described above by using a conductor pattern for an inductor as an example. The present invention is not limited to this and the present invention can be applied to a conductor pattern such as a stripline pattern for various electronic components.

In the exposure processes of preferred embodiments described above, evaluation results of the conductor pattern 5 for the inductor are shown in Table 1, wherein in the image pattern 3a of the photo-mask 3, the exposures were performed when the line width of the straight line was about 25 μm and the space was about 15 μm , while patterns with various line widths of the corner were used. The evaluations of peeling of the corner 5b of the conductor pattern 5 were performed for the inductor during burning and evaluations of Q degradation of the obtained multi-layer inductor 25 were performed after wet-proof loading. The Q degradation was accepted when the Q value of the obtained multi-layer inductor 25 after wet-proof loading (70°C, 95 %RH, 2000 Hrs) was within $\pm 10\%$ of the initial value. In Table 1, the evaluation results are also shown by way of comparison, in which exposure was performed when using an image pattern 3a having the same line widths of the corner

and the straight line.




TABLE 1

	First Preferred Embodiment	Second Preferred Embodiment	Third Preferred Embodiment	Conventional Example
Cross-sectional size of straight line after burning (μm)				
Cross-sectional size of corner after burning (μm)				
Bottom face width/Conductor thickness	1.5	1.33	1.07	0.87
Peeling	No	No	No	Yes
Q degradation after wetproof loading	0/100	1/100	3/100	

It is understood from Table 1 that when the bottom surface cross-sectional width W_1 of the corner of the conductor pattern 5 for the inductor is about 1.07 times the conductor thickness D or more, peeling of the corner 5b is prevented and Q degradation is also minimized. In particular, when the bottom surface cross-sectional width W_1 of the corner was about 1.5 times the conductor thickness D or more, Q degradation did not occur.

When the bottom surface width W1 of the straight line 5a of the conductor pattern 5 for the inductor is excessively reduced, meandering of the straight line 5a is liable to be generated after burning. In order to suppress the meandering, the relationship between the bottom surface width W1 of the straight line 5a and the conductor thickness D was evaluated. The evaluation results are shown in Table 2.

TABLE 2

	Fourth Preferred Embodiment	Fifth Preferred Embodiment
Cross-sectional size of corner after burning (μm)	<div>26.25</div> <div></div> <div>15.75</div>	
Cross-sectional size of straight line after burning (μm)	<div>18.2</div> <div></div> <div>7.7</div>	<div>17.5</div> <div></div> <div>7</div>
Bottom face width/Conductor thickness	0.73	0.67
Meandering	No	Yes

It is understood from Table 2 that when the bottom surface width W1 of the straight line 5a is greater than approximately 0.67 times the conductor thickness D, the meandering of the straight line 5a is reliably prevented.

While the present invention has been particularly shown and described with reference to preferred embodiments thereof, it will be understood by those skilled in the art that the foregoing and other changes in form and details can be made without departing from the spirit and scope of the present invention.

100 101 102 103 104 105 106 107 108 109 110 111 112 113 114 115 116 117 118 119 120 121 122 123 124 125 126 127 128 129 130 131 132 133 134 135 136 137 138 139 140 141 142 143 144 145 146 147 148 149 150 151 152 153 154 155 156 157 158 159 160 161 162 163 164 165 166 167 168 169 170 171 172 173 174 175 176 177 178 179 180 181 182 183 184 185 186 187 188 189 190 191 192 193 194 195 196 197 198 199 200 201 202 203 204 205 206 207 208 209 210 211 212 213 214 215 216 217 218 219 220 221 222 223 224 225 226 227 228 229 230 231 232 233 234 235 236 237 238 239 240 241 242 243 244 245 246 247 248 249 250 251 252 253 254 255 256 257 258 259 260 261 262 263 264 265 266 267 268 269 270 271 272 273 274 275 276 277 278 279 280 281 282 283 284 285 286 287 288 289 290 291 292 293 294 295 296 297 298 299 300 301 302 303 304 305 306 307 308 309 310 311 312 313 314 315 316 317 318 319 320 321 322 323 324 325 326 327 328 329 330 331 332 333 334 335 336 337 338 339 340 341 342 343 344 345 346 347 348 349 350 351 352 353 354 355 356 357 358 359 360 361 362 363 364 365 366 367 368 369 370 371 372 373 374 375 376 377 378 379 380 381 382 383 384 385 386 387 388 389 390 391 392 393 394 395 396 397 398 399 400 401 402 403 404 405 406 407 408 409 410 411 412 413 414 415 416 417 418 419 420 421 422 423 424 425 426 427 428 429 430 431 432 433 434 435 436 437 438 439 440 441 442 443 444 445 446 447 448 449 450 451 452 453 454 455 456 457 458 459 460 461 462 463 464 465 466 467 468 469 470 471 472 473 474 475 476 477 478 479 480 481 482 483 484 485 486 487 488 489 490 491 492 493 494 495 496 497 498 499 500 501 502 503 504 505 506 507 508 509 510 511 512 513 514 515 516 517 518 519 520 521 522 523 524 525 526 527 528 529 530 531 532 533 534 535 536 537 538 539 540 541 542 543 544 545 546 547 548 549 550 551 552 553 554 555 556 557 558 559 560 561 562 563 564 565 566 567 568 569 570 571 572 573 574 575 576 577 578 579 580 581 582 583 584 585 586 587 588 589 590 591 592 593 594 595 596 597 598 599 600 601 602 603 604 605 606 607 608 609 610 611 612 613 614 615 616 617 618 619 620 621 622 623 624 625 626 627 628 629 630 631 632 633 634 635 636 637 638 639 640 641 642 643 644 645 646 647 648 649 650 651 652 653 654 655 656 657 658 659 660 661 662 663 664 665 666 667 668 669 670 671 672 673 674 675 676 677 678 679 680 681 682 683 684 685 686 687 688 689 690 691 692 693 694 695 696 697 698 699 700 701 702 703 704 705 706 707 708 709 710 711 712 713 714 715 716 717 718 719 720 721 722 723 724 725 726 727 728 729 730 731 732 733 734 735 736 737 738 739 740 741 742 743 744 745 746 747 748 749 750 751 752 753 754 755 756 757 758 759 760 761 762 763 764 765 766 767 768 769 770 771 772 773 774 775 776 777 778 779 780 781 782 783 784 785 786 787 788 789 790 791 792 793 794 795 796 797 798 799 800 801 802 803 804 805 806 807 808 809 810 811 812 813 814 815 816 817 818 819 820 821 822 823 824 825 826 827 828 829 830 831 832 833 834 835 836 837 838 839 840 841 842 843 844 845 846 847 848 849 850 851 852 853 854 855 856 857 858 859 860 861 862 863 864 865 866 867 868 869 870 871 872 873 874 875 876 877 878 879 880 881 882 883 884 885 886 887 888 889 890 891 892 893 894 895 896 897 898 899 900 901 902 903 904 905 906 907 908 909 910 911 912 913 914 915 916 917 918 919 920 921 922 923 924 925 926 927 928 929 930 931 932 933 934 935 936 937 938 939 940 941 942 943 944 945 946 947 948 949 950 951 952 953 954 955 956 957 958 959 960 961 962 963 964 965 966 967 968 969 970 971 972 973 974 975 976 977 978 979 980 981 982 983 984 985 986 987 988 989 990 991 992 993 994 995 996 997 998 999 1000